

# BlackBaller – Extreme Mobile Filter

Call/SMS/MMS

2004 © Killer Mobile

BlackBaller is the first program for the Nokia Series 60 mobile phones that offers SMS/MMS filtering.

BlackBaller introduces the new “Smart Reject Sensor”™ system which allows you to modify your filter lists on the fly.



## Protect yourself from unwanted calls and messages

*“Have you been BlackBalled?”*

BlackBaller is an Extreme Mobile Filter that is designed to block (reject) unwanted calls and messages (SMS/MMS). BlackBaller is a full featured and easy to use program which offers unique features such as message filtering, and the ultimate in user friendly features - “Smart Reject Sensor”™. BlackBaller is the most user friendly and robust program of its kind.

### *BlackBaller feature Summary:*

- Block unwanted calls and messages (SMS/MMS)
- Supports two types of filters: Blacklists (Blocks all calls on list) and Whitelists (Blocks all calls except what are on the list).
- Tight integration with phonebook. Availability to block groups, persons, numbers and private numbers. Also includes an advanced option for setting block expiration date.
- “Smart Reject Sensor”™ - Ultimate ergonomic solution. When you reject a call the system automatically asks if you want to block this specific caller.
- The real background mode. BlackBaller is highly integrated into your mobile device. It works silently without keeping the program open and hidden and using up a lot of system resources.
- Complete log for rejected calls/messages.

**Note:** BlackBaller works on Nokia Series 60 based smartphones. The program was fully tested on the Nokia 7650/3650/6600 devices. It should work on other series 60 devices. Please test the program on your mobile device prior purchasing

**Note:** BlackBaller offers a trial period of 14 days. After that time you should register your copy of the program, otherwise you will not be able to continue using it. Killer Mobile is not responsible for any lost personal data that you have entered into BlackBaller during the trial period.

Visit our site for more details: <http://www.killermobile.com>

Contact us in case you have additional questions: [info@killermobile.com](mailto:info@killermobile.com)

## Getting Started

Install the BlackBaller.SIS installation package on your mobile device. Installation process is the same on all Series 60 phones. After installation is complete the BlackBaller icon will be listed in the phones menu. Run the program by pressing the joystick on its icon. First you will see the program logo for a few seconds, and then the program startup screen will be displayed. The initial list of filters will be empty. You need to create the new list. At the status bar you will see the text '[On] 0 list(s)', this means that BlackBaller is switched on




(enabled, otherwise there will be displayed '[Off]'), and currently there are no lists. Press the right softkey to display the 'Options' menu pane. Select the 'List' menu item, and there press the 'New' sub-item. This will initiate the new list creation. There will appear a dialog where you should set up the list options. The first option is the list name. The default list name will be assigned unless you specify a new one. The second option is the list type. There are two types of list: 'Blacklist' and 'Whitelist'. Blacklist means that all numbers/person/groups specified in the list will be blocked. Whitelist works using the opposite logic. All entries that are listed in whitelist will not be blocked; all other numbers will be blocked. The third option is 'Use to filter', when you press this option the checkbox list will pop up. There are two items: 'Call' and 'SMS/MMS'. If you check 'Call' item then this list will filter all incoming calls, if you check 'SMS/MMS' item, then the list will filter

all received SMS and MMS messages. If you check both items then the list will be used to filter both calls and messages. You can change these options later if you wish. When you finish setting the new list options press the right softkey 'Back'. Your newly created list will now be available. At the left side is the list type: 'Black', then comes list name 'My list', and at the right side there are two small icons: 1. Envelope, which indicates that this list is an active list that is used for SMS/MMS message filtering 2. Phone, which indicates that the list is an active list that is used for filtering calls.



Next you need to add some entries to the list, the numbers/persons/groups that you want to block. Press the joystick on the list. And the program will go in the list edit mode. Currently the list is empty, and you will see '(no entries)' text on the screen. On the status pane there is displayed list name 'My list', and the entries count in the square braces '[0]'. Press the left softkey to display the 'Options' menu pane. Here are the commands for adding numbers/persons/groups to the list. When you complete your list you can exit from the program, BlackBaller will work according to the list that you have specified and will reject all calls/messages from blocked callers.

BlackBaller introduces an ultimate ergonomic solution - "Smart Reject Sensor"™. In order to make "Smart Reject Sensor"™ work you should have active list (black or white) for filtering incoming calls. Here is how it works.



**And now you are safe, no more calls will disturb  
you from 'Dracula'**

## Detailed Description

Main view of the BlackBaller program has the following menu commands:



- **'List -> New'** Creates new filter list
- **'List -> Edit'** Edit the content of an existing list
- **'List -> Delete'** Deletes the selected list
- **'List -> Options'** View/Change list options (name, type and filter flags).
- **'View log'** Display complete log of rejected calls/messages
- **'Disable/Enable'** Disables/Enables the call and message filtering.
- **'Settings'** View/Change the program settings
- **'Program -> Register'** Register your copy of the program. The registration dialog will be activated. You will be prompted with your phones IMEI number and the text box for the registration key. You should enter the correct registration key.
- **'Program -> About'** Display the information about the program
- **'Exit'** Exit the program. BlackBaller works in a real background mode. You can safely exit the program after you finish working with the filter lists.


List edit view of the BlackBaller program has the following menu commands:

- **'Add number -> From contacts'** Choose a number from the phonebook and add it to the list.
- **'Add number -> Enter manually'** Enter the number manually and add it to the list
- **'Add number -> Private number'** Add private number to the list
- **'Add person'** Select a person from the phonebook and add it to the list
- **'Add group'** Select a group from the phonebook and add it to the list
- **'Delete'** Delete list entry
- **'Mark/Unmark'** Standard Mark/Unmark commands
- **'Entry options'** View/Change list entry options (expiration date, enabled)





1. Active list entry




2. Expired list entry



3. Disabled list entry

List entry options:



- Use permanently (Yes/No). If you choose 'No' there will be given an option for setting expiration date.
- Expiration Date. This option is hidden when 'Use permanently' is set to 'Yes'.
- Enabled (Yes/No). With this option you can disable/enable list entry



Settings dialog:



- Smart reject sensor (Enabled/Disabled). Turn "Smart Reject Sensor"™ feature on/off.
- Log duration (No log/1 day/10 days/30 days). Sets the interval where the log of the rejected calls and messages will be collected.
- Mute SMS/MMS sound (Yes/No). When set to 'Yes' the program will correctly handle 'SMS received' sound and you will not hear the message notification sound in case of the blocked message. This is a default, recommended behavior.

Copyright 2004 Killer Mobile - All Rights Reserved  
[www.killermobile.com](http://www.killermobile.com)  
[info@killermobile.com](mailto:info@killermobile.com)